

# BAE Secura OPzS-N6/N7 Block

1.75 VPC

DISCHARGE RATINGS IN AMPS @ 77°F (25°C)

Battery	1'	30'	1 h	2 h	3 h	4 h	5 h	6 h	8 h	10 h	12 h	24 h
12V 1 OPzS 50-N6/N7	90.8	43.7	29.2	18.1	14.1	11.3	9.6	8.3	6.6	5.6	5.0	2.8
12V 2 OPzS 100-N6/N7	167.0	85.5	57.7	35.9	28.0	22.5	18.8	16.3	13.0	10.8	9.8	5.5
12V 3 OPzS 150-N6/N7	235.0	126.5	86.7	54.2	42.6	34.2	28.7	25.0	19.9	16.6	15.0	8.4
6V 2 OPzS 100-N6/N7	167.0	85.5	57.7	35.9	28.0	22.5	18.8	16.3	13.0	10.8	9.8	5.5
6V 3 OPzS 150-N6/N7	235.0	126.5	86.6	54.2	42.5	34.2	28.7	25.0	19.9	16.6	15.0	8.4
6V 4 OPzS 200-N6/N7	294.0	165.6	114.7	72.2	56.7	45.5	38.3	33.2	26.5	22.2	20.0	11.1
6V 5 OPzS 250-N6/N7	345.0	203.8	142.0	90.0	70.9	56.9	47.9	41.6	33.1	27.7	25.0	13.9
6V 6 OPzS 300-N6/N7	393.0	240.2	169.3	107.4	85.0	68.4	57.5	49.9	39.7	33.3	30.0	16.7

1.81 VPC

DISCHARGE RATINGS IN AMPS @ 77°F (25°C)

Battery	1'	30'	1 h	2 h	3 h	4 h	5 h	6 h	8 h	10 h	12 h	24 h
12V 1 OPzS 50-N6/N7	66.9	38.0	26.7	17.1	13.5	10.9	9.3	8.1	6.5	5.5	4.9	2.7
12V 2 OPzS 100-N6/N7	122.7	73.7	52.2	33.8	26.8	21.6	18.3	15.9	12.8	10.7	9.7	5.4
12V 3 OPzS 150-N6/N7	173.7	108.3	78.0	51.0	40.5	32.8	27.8	24.3	19.4	16.3	14.7	8.2
6V 2 OPzS 100-N6/N7	122.7	73.7	52.2	33.8	26.8	21.6	18.3	15.9	12.8	10.7	9.7	5.4
6V 3 OPzS 150-N6/N7	171.7	108.3	77.9	50.9	40.5	32.8	27.8	24.2	19.4	16.3	14.7	8.2
6V 4 OPzS 200-N6/N7	217.0	141.1	101.9	67.5	53.9	43.8	37.1	32.3	25.9	21.8	19.6	10.9
6V 5 OPzS 250-N6/N7	255.0	172.0	126.5	83.9	67.1	54.5	46.3	40.3	32.4	27.2	24.5	13.7
6V 6 OPzS 300-N6/N7	290.0	202.9	149.2	100.1	80.4	65.4	55.4	48.3	38.8	32.5	29.4	16.4



# BAE *Secura OPzS-N6/N7 Block*

1.85 VPC

DISCHARGE RATINGS IN AMPS @ 77°F (25°C)

Battery	1'	30'	1 h	2 h	3 h	4 h	5 h	6 h	8 h	10 h	12 h	24 h
<b>12V 1 OPzS 50-N6/N7</b>	51.1	32.9	23.8	15.8	12.7	10.4	8.9	7.7	6.2	5.2	4.7	2.6
<b>12V 2 OPzS 100-N6/N7</b>	94.3	63.7	46.4	31.0	25.0	20.4	17.4	15.2	12.2	10.3	9.3	5.2
<b>12V 3 OPzS 150-N6/N7</b>	133.0	92.8	69.0	46.6	37.8	30.9	26.4	23.0	18.5	15.6	14.1	7.9
<b>6V 2 OPzS 100-N6/N7</b>	94.3	63.7	46.4	31.0	25.0	20.4	17.4	15.2	12.2	10.3	9.3	5.2
<b>6V 3 OPzS 150-N6/N7</b>	131.0	92.8	68.8	46.6	37.7	30.9	26.4	23.0	18.5	15.6	14.1	7.9
<b>6V 4 OPzS 200-N6/N7</b>	166.0	121.0	90.4	61.6	50.1	41.1	35.0	30.7	24.8	20.8	18.8	10.5
<b>6V 5 OPzS 250-N6/N7</b>	195.0	147.4	111.0	76.3	62.3	51.2	43.7	38.3	30.8	26.0	23.5	13.1
<b>6V 6 OPzS 300-N6/N7</b>	223.0	172.9	131.0	90.9	74.4	61.2	52.3	45.9	37.0	31.2	28.2	15.7

